

# Embedded device user auto-logout timeout

## HP Futuresmart

- In a web browser, go to the printer's web interface.
- Sign in to the **Administrator settings**.
- Click **General**.
- Under **Control Panel Customization**, click **Display Settings**.
- Enter a value in the **Inactivity Timeout** textbox and click **Apply**.

## Konica Minolta

The no-activity timeout will move any screen back to the default screen and if it's already on the default screen it will log the user out. To change this setting:

- In a web browser, go to the printer's web interface.
- Sign in to the **Administrator settings**.
- Click **System Settings > Reset Settings > System Auto Reset**.
- Enter the number of minutes of no activity after which the user will be auto-logged out in the **System Auto Reset Time** textbox.
- Click **OK**.

## Lexmark

- In a web browser, go to the printer's web interface.
- In the left menu option list, click **Settings**.
- Click **Device**.
- Expand **Preferences**.
- Change the value in the **Screen Timeout** textbox.
- Click **Save**.

Document revision date: 2024/10/15

Software version: 2.4.18.0

© 2024 Blue Swift Software CC